

(12) INTERNATIONAL PUBLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau




(43) International Publication Date
8 April 2004 (08.04.2004)

PCT

(10) International Publication Number
WO 2004/030232 A1

- (51) International Patent Classification⁷: **H04B 1/16** (74) Agents: **DUNLOP, Hugh, Christopher et al.**; R.G.C. Jenkins & Co, 26 Caxton Street, London SW1H 0RJ (GB).
- (21) International Application Number: **PCT/GB2003/004179** (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SD, SE, SG, SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VN, YU, ZA, ZM, ZW.
- (22) International Filing Date: **24 September 2003 (24.09.2003)**
- (25) Filing Language: **English**
- (26) Publication Language: **English**
- (30) Priority Data: **0222379.0** **26 September 2002 (26.09.2002)** **GB**
- (71) Applicant (*for all designated States except US*): **QUALCOMM (UK) LIMITED** [GB/GB]; Spectrum Point, 2nd Floor, 279 Farnborough Road, Farnborough, Hampshire GU14 7LS (GB).
- (72) Inventor; and
- (75) Inventor/Applicant (*for US only*): **SMITH, Alan, Andrew** [GB/GB]; Qualcomm (UK) Limited, Spectrum Point, 2nd Floor, 279 Farnborough Road, Farnborough, Hampshire GU14 7LS (GB).
- (84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).
- Published:**
— *with international search report*
- For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.*

(54) Title: METHOD OF AND APPARATUS FOR REDUCING FREQUENCY ERRORS ASSOCIATED WITH AN INTER-SYSTEM SCAN



(57) Abstract: A plural-mode receiver (10) is able to receive signals from a first communication system (e.g. WCDMA) or signals from a second, different communication system (e.g. GSM). The receiver (10) comprises a first receiver chain (13, 15, 17, 19) for receiving signals of the first communication system and a second receiver chain (12, 14, 16, 18) for receiving signals of the second communication system. A reference oscillator (24) is arranged to generate a reference signal for the first receiver chain and the second receiver chain. The receiver also comprises a controller (22) for controlling the reference oscillator (24) so that the oscillator (24) oscillates at frequencies related to signals of the first communication system or signals of the second communication system. The controller (22) records the change in frequency of the oscillator (24) resulting from changing to the frequencies related to signals of the second communication system and a period of time during which signals of the second communication system are received by the second receiver chain. The controller (22) then calculates from the recorded change and the recorded period of time an error vector and changes parameters of the reference oscillator (24), including applying the calculated error vector, so that the oscillator oscillates at frequencies related to signals of the first communication system.

WO 2004/030232 A1

METHOD OF AND APPARATUS FOR REDUCING FREQUENCY ERRORS ASSOCIATED WITH AN INTER-SYSTEM SCAN

BACKGROUND OF THE INVENTION

I. Field of the Invention

The invention relates generally to a method of and apparatus for reducing frequency errors associated with an inter-system scan. The invention is useful for reducing frequency error when performing an intersystem scan between a continuous frequency division duplex system, for example a WCDMA system, and a differently duplexed system, for example a time division duplex system such as GSM, but is not limited to such an application.

II. Description of the Related Art

In the following, reference will be made to the WCDMA and GSM standards, but it will be appreciated by those possessed of the relevant skills that the invention is not limited to those standards and may be applied to inter-system scans between other different communication systems. The terms "mobile unit" and "mobile phone" are also used and, of course, cover mobile phones, but also cover other devices capable of communicating with a cellular system in the transfer of voice or information data.

Most if not all equipment used in communications systems includes an internal frequency reference circuit that is adjustable to allow the equipment to adjust the timing of its operations to align with that of other equipment within the communications system. For example in a cellular telephone system the mobile units include a reference frequency circuit, which is commonly an adjustable oscillator whose output frequency can be trimmed within a specified range using an control voltage input, to enable the timing within the mobile unit to be aligned with that of the serving cell or network. The frequency reference circuit is commonly a phase-locked loop based around a voltage controlled temperature compensated crystal oscillator (VCTCXO), an accurate oscillator that allows the range to be specified in terms of parts per million (ppm).

The mobile unit will, of course, be in communication with the system when it is active during a call. The system needs to "know" where the mobile unit is when it is not

receiving or making a call so that incoming messages can be sent to it. Mobile units therefore continue to operate in an idle mode when a call is not being made so that data can be paged to it from time to time. The mobile unit has to maintain time alignment with the WCDMA system, in order to correctly monitor for paging data from the system for the mobile unit. The VCTCXO and phase-locked loop are usually very accurate and need only be subjected to very minor corrections, essentially remaining at a constant frequency while the phone remains in active or idle communication with the system.

During certain situations, for example when leaving the coverage area of an initial system and entering the coverage area of a new system, it becomes necessary to monitor the signals of the surrounding cells belonging to the new system so that a controlled handover can take place between the two systems. While it would be possible to do this from within the system, such an approach would place an undue burden on the system because it would have to monitor both active and idle mobile units. The mobile units themselves therefore do this monitoring.

There are many different standards available for use in cellular communications systems including the widely established GSM standard and the newer CDMA standards including WCDMA. System users expect to have continuous service even when they roam outside the area of coverage of the service company to which they subscribe. In order to meet this expectation, so called multi-mode phones have been developed that are capable of communication in, say, both a WCDMA system and a GSM system.

The continuous nature of WCDMA signals means that there is no natural break in the signals that would allow scanning for signals from other systems. Furthermore, there is no common synchronization between a WCDMA system and a GSM system. Different systems are asynchronous in that there is no predefined relationship between the timing and phase of the signals of the systems.

One way of overcoming this would be to apply a post-reception phase correction to the data before decoding is done. This could be done by using a hardware rotator to correct for phase offset as the received data is sampled, i.e. receive a sample, rotate it and then store it in memory for decoding. A problem with this approach is that a hardware rotator requires additional hardware, and hence uses extra silicon area, and

therefore adds additional cost and complexity to the circuit (which is usually provided in the form of an ASIC).

Another way would be to rotate the received samples in memory before the decoding takes place, i.e. bring in all of the samples and then apply a rotation algorithm. A problem with this approach is that a signal processing rotation algorithm such as this requires code to be written, memory in which to store it and a DSP (digital signal processor) powerful enough to run it in the required time. This approach therefore consumes DSP memory and energy from the battery.

One proposal for the WCDMA standard to overcome this problem is to use a method known as compressed mode to create "free-space" periods during which the receiver can be re-configured to scan for other systems. Thus, during a free space period, the receiver is tuned to a GSM channel and a measurement of characteristics of the channel is performed. At the end of a "free-space" period, the receiver must be configured back to the WCDMA channel of the original system in order to ensure uninterrupted service. In order to do this, the receiver needs to be phase locked before reception is attempted. Therefore, the phase-locked loop (or other reference oscillator) must be re-tuned and re-synchronized both when changing the phone from WCDMA to GSM and when changing the phone from GSM back to WCDMA.

When the phone is retuned to scan for other serving systems, a number of actions have to occur:

1. Initialize receiver and re-program PLL to new (GSM) frequencies.
2. Scan for data to give coarse frequency synchronization.
3. Scan for data to give fine frequency correction.
4. Decode GSM system access parameters.
5. Re-configure receiver and re-program PLL to original (WCDMA) frequencies.
6. Re-acquire and re-synchronize to the WCDMA system.

This retuning results in a frequency error being introduced into the synchronization of the phone to the WCDMA system, making the re-acquisition more difficult when returning to the WCDMA channel. One proposal for reducing this problem when switching between GSM and WCDMA modes is to extend the free space period as much as possible for the GSM scan, to minimize the response time of circuits,

and to rely on the receiver to re-synchronize using an frequency or time tracking auto frequency control (AFC) algorithm.

However, this approach is not entirely satisfactory at least for the following reason. When the scanning for data occurs in the above actions 2 and 3, the phase-locked loop is fine-tuned using a control voltage input. This fine-tuning results in a frequency error being introduced into the synchronization when the phone is reconfigured to return to the WCDMA system in the above action 5. Consequently, the re-acquisition in action 6 is more difficult to perform.

SUMMARY OF THE INVENTION

The invention addresses the above-discussed and related problems.

According to one aspect of the invention there is provided a method of controlling a plural-mode receiver, capable of receiving signals from a first communication or signals from a second, different communication system, to reduce frequency errors associated with the receiver scanning for signals of the second communication system while receiving signals of the first communication system, the method comprising: changing parameters of a reference oscillator of the receiver so that the oscillator oscillates at frequencies related to signals of the second communication system; recording the change in frequency of the oscillator resulting from the adjustment; receiving signals of the second communication system for a period of time; recording the period of time; calculating from the recorded change and the recorded period of time an error vector; and changing parameters of the reference oscillator, including applying the calculated error vector, so that the oscillator oscillates at frequencies related to signals of the first communication system.

According to another aspect of the invention there is provided a plural-mode receiver apparatus for receiving signals from a first communication or signals from a second, different communication system, the apparatus comprising: a first receiver chain for receiving signals of the first communication system; a second receiver chain for receiving signals of the second communication system; a reference oscillator for generating a reference signal for the first receiver chain and the second receiver chain; and a controller for: changing parameters of the reference oscillator so that the oscillator

oscillates at frequencies related to signals of the second communication system; recording the change in frequency of the oscillator resulting from the adjustment; recording a period of time during which signals of the second communication system are received by the second receiver chain; calculating from the recorded change and the recorded period of time an error vector; and changing parameters of the reference oscillator, including applying the calculated error vector, so that the oscillator oscillates at frequencies related to signals of the first communication system.

According to a further aspect of the invention there is provided a receiver for receiving signals of a first communication system and signals of a second communication system, the receiver comprising a receiving circuit tunable to receive signals of the first and second communication systems, the receiver being arranged so that, while tuned to receive signals of the first communication system, the receiving circuit can be briefly retuned to receive signals of the second communication system before being tuned back to receive again signals of the first communication system, and so that a correction is made when tuning back to signals of the first communication system depending on tuning changes made while retuning and receiving signals of the second communication system and the duration of the changes.

The invention also provides a method of receiving signals of a first communication system and signals of a second communication system, the method comprising tuning a receiving circuit to receive signals of the first communication system, retuning the receiver circuit to receive signals of the second communication system, tuning the receiver back to receive again signals of the first communication system, determining tuning changes made while retuning and receiving signals of the second communication system and the duration of the changes, calculating from the changes and duration of the changes a correction to be made to the tuning, and making the calculated correction when tuning back to signals of the first communication system.

As will be appreciated from the following description of a receiver in which the invention is embodied, if the reference oscillator is allowed temporarily to achieve phase lock with the new system and just receive the samples as normal, i.e. allow the reference oscillator to become phase locked before starting the received data sampling, then the received samples will have the correct phase and no post correction will be

required. This approach requires very little overheads in circuit complexity, memory space and energy consumption.

Furthermore, the problem of maintaining phase lock with the continuous frequency division duplex (e.g. WCDMA) system while temporarily achieving phase lock with the GSM system is overcome or at least mitigated by estimating the error induced by retuning to the time division duplex (e.g. GSM) system in order to apply a correction for it before the WCDMA system is re-acquired. The correction can be computed before (or during) the inter-system scan and applied during the receiver re-configuration period, so that when the WCDMA system is re-acquired, the error will already have been substantially reduced.

The above and further features of the invention are set forth with particularity in the appended claims and together with advantages thereof will become clearer from consideration of the following detailed description of an exemplary embodiment of the invention given with reference to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

In the drawings:

Figure 1 is a schematic circuit diagram of a dual mode receiver for a mobile unit;

Figure 2 is a schematic circuit diagram of a phase-locked loop in the receiver of Figure 1;

Figure 3 is a phase diagram in PN space;

Figure 4 is a graph showing energy curves in PN space; and

Figure 5 shows one example of a timeline for an inter-system scan performed by the receiver of Figure 1.

DETAILED DESCRIPTION OF AN EMBODIMENT OF THE INVENTION

Figure 1 is a schematic circuit diagram representing a dual mode receiver 10 for a mobile unit. For the purpose of explanation the dual mode receiver 10 is illustrated as being capable of receiving either WCDMA or GSM signals. It will be appreciated that

other combinations of receivable signals are possible. Signals received at an antenna 11 are switched by a switching component 12 to either a WCDMA receiver chain (shown in the upper part of Figure 1) or a GSM receiver chain (shown in the lower part of Figure 1). Both receiver chains operate in essentially the same way insofar as the received signal is: filtered by a bandpass filter (BPF) 13,14; amplified by a low noise amplifier 15,16; down-converted to a baseband frequency by a down-converter 17,18; and filtered by a lowpass filter 19,20 before being input to a baseband circuit and controller 22 for further processing.

The receiver 10 also comprises a voltage controlled temperature compensated crystal oscillator (VCTCXO) 24 that provides a reference frequency signal to a phase-locked loop. The phase-locked loop comprises a phase-locked loop integrated circuit (PLL) 25 (to be described in detail herein below), a loop filter 26 and a voltage-controlled oscillator 27. The phase-locked loop generates a signal at a suitable frequency to enable the down-converter 17, 18 in both the WCDMA and GSM receiver chains to down-convert the received signals to a baseband level. This use of a phase-locked loop is well known and need not be described in greater detail herein.

In addition to the aforementioned processing of down-converted signals, the baseband circuit and controller 22 also controls operation of the receiver 10. The baseband circuit and controller 22 typically comprises a control processor (not shown) that generates signals to cause the antenna switching component 12 to switch between the WCDMA chain and the GSM chain at the required time. The controller-generated signals are applied to, among other things, the antenna switching component 12 and a PLL switching controller 28, which controls operation of the phase-locked loop.

Normally, a dual-mode receiver circuit would require a separate phase-locked loop for each of the WCDMA and GSM receiver chains. However, as shown in Figure 1, a single switchable phase-locked loop of the kind described in international (PCT) patent application PCT/GB01/05610 may advantageously be used to provide a signal to either of the down-converter 17, 18 in the WCDMA and GSM receiver chains since the two receiver chains are never required to operate simultaneously.

Figure 2 of the accompanying drawings is a schematic circuit diagram representing in greater detail the PLL 25 of Figure 1. The PLL 25 shown in Figure 2 may be essentially the same as described in the aforementioned international (PCT)

patent application PCT/GB01/05610. The PLL 25 comprises a programmable divide-by-R counter 31, a programmable divide-by-N counter 32 and a phase detector 33. The divide-by-R counter 31 is driven by the VCTCXO (see Figure 1). Two register sets 35,36, each store data defining a respective configuration for the PLL 25. Each register set 35,36 has an associated serial/parallel converter 37,38 connected to receive data in serial form from the baseband circuit and control 22 via a serial data interface 39. Each register set 37,38 comprises a register 37R,38R for holding data for the divide-by-R counter 31, a register 37N,38N for holding data for the divide-by-N counter 32 and a register 37P,38P for holding data for the phase detector 33. The phase detector data in the registers 37P,38P defines the gain applied by the phase detector 33.

Also shown in Figure 2 is a lock detector 40 coupled to the phase detector 33 for providing an indication to the baseband circuit and control 22 when the PLL 25 has locked onto the desired frequency, i.e. when it has become stable. Switches 42,43 and 44 are provided to switch the divide-by-R counter 31, the divide-by-N counter 32 and the phase detector 33 between the two register sets 37,38. A further switch 45 is provided to switch the serial data interface 39 from the baseband circuit and control 22 between the two serial to parallel converters 37,38. All of the switches 42 to 45 are controlled by a configuration select control signal 46 generated by the baseband circuit and controller 22.

The switches are arranged so that when the first register set 35 is coupled to the divide-by-R counter 31, the divide-by-N counter 32 and the phase detector 33, the second register set 36 is coupled via the switch 45 to the serial data interface 39 from the host microcontroller, and when the second register set 36 is connected to the divide-by-N counter 17, etc, the first register set 35 is connected to the serial data interface 39. In this way, one set of registers 36,37 can be loaded with new data while the other set of registers 36,37 is controlling operation of the divide-by-N counter 31, etc. This provides an efficient way of switching between different frequencies by reducing the amount of time that the PLL is inactive.

Figure 3 of the accompanying drawings is a phase diagram in PN space, where the circumference of the circle 50 represents an entire PN sequence. Only part of the PN sequence is assigned to a mobile unit and that part is centered in a search window W. When the phase (in PN space) of the signal generated by the phase-locked loop is

centered on the window W at code position β the energy (E_b/N_o) in the received signal will be at a maximum. This is represented by the energy curve E_1 in Figure 4. When the phase of the signal from the phase-locked loop changes so that the signal is off center in the window W at position $\beta - \Delta e$ the energy (E_b/N_o) in the received signal will be at a lower level as represented by the curve E_2 in Figure 4. As long as the phase of the signal from the phase-locked loop does not move out of the search window W , the signal will be recoverable, even at a lower level of energy. However, if the phase changes to the extent that the signal lies outside the search window W , the receiver will no longer be locked onto the received signal and reception will be lost. Put another way the value of Δe should not be greater than $\frac{1}{2}W$.

The receiver of Figure 1 includes correlators (not shown) that correlate PN sequences in the received WCDMA signals with internally generated PN sequences in order to extract the correct data from the WCDMA signals. If the clock source for the correlator (i.e. the phase-locked loop) is made to run faster than necessary, the PN generators will advance too quickly and, the correlation peak will appear to be behind in time. If the clock is made to run slow, the correlation peak will appear to be ahead in time because the PN generators will be running slower than expected. This can be thought of as the correlation peak "jumping" from its aligned position to another position in the search window by an amount which is proportional to the net frequency error introduced by the alternate system scan.

When a mobile unit is in standby the frequency of the VCTCXO and hence the phase-locked loop may well drift away from the frequency of the WCDMA system. This will occur because of tolerances of manufacture and changes in the environment in which the mobile unit is located. As long as the drift does not result in a code phase difference greater than $\frac{1}{2}W$, the mobile unit will be able to synchronize with the system when it comes out of the standby state. Mobile units are designed so that the drift is less than $\frac{1}{2}W$.

As has been mentioned previously herein, the continuous nature of WCDMA signals means that there is no natural break in the signals that would allow scanning for signals from other systems. When a mobile unit is required to monitor the strength of signals from cells in a new system, the mobile unit has to receive and decode signals from the surrounding cells of the new system and process the network information

carried by those signals. In order to do this, the receiver needs either to be phase locked before reception is attempted or to apply a post-reception phase correction to the data before decoding is done.

This is done in the receiver of Figure 1 by allowing the phase-locked loop temporarily to achieve phase lock with the GSM signals before starting the received data sampling. This ensures that samples have correct phase and no post correction is required. When a mobile unit is in a steady WCDMA idle state, the VCTCXO and phase-locked loop are both frequency and phase locked to the WCDMA system. While in the idle state the mobile unit will "wake up" periodically to monitor its assigned paging messages from the WCDMA system. Therefore when scanning for GSM signals any induced frequency and phase errors introduced on to the reference oscillator by the surrounding cell scans must be corrected before the mobile unit next "wakes up" to monitor for WCDMA system paging message.

The phase-locked loop is therefore allowed to achieve lock using known automatic frequency control (AFC) techniques and while doing so, the magnitude and direction of the induced errors (an error vector) is monitored together with the durations that the errors are applied for. By summing these error vectors, a resultant error vector can be found and then used to apply a nullifying error of equal and opposite magnitude to the VCTCXO (see Figure 1). Thus, by the time that the mobile unit next has to "wake up" to monitor for WCDMA system paging data, the VCTCXO and phase-locked loop will once again be aligned for the WCDMA system, as if no other activity had occurred.

Figure 5 of the accompanying drawings shows one example of a timeline for an inter-system scan performed by the receiver of Figure 1. The timeline covers an initial state 51 and seven intervals labeled 52 to 58. Lines 61 and 62 represent frequency (VCTCXO frequency) and time axes respectively. In the initial state 51 the receiver is tuned to receive, and is receiving, WCDMA signals. In this state the frequency is at f_w , the receive frequency for the WCDMA signal.

In interval 52 which lasts for a time period T_{PLL1} the receiver of Figure 1 is initialized with data that will subsequently enable the GSM receiver chain to receive signals from a GSM system. The period of time T_{PLL1} depends on characteristics of the phase-locked loop, but once the phase-locked loop has been designed this period will be essentially constant. Interval 53 represents the time T_{fc} taken for the receiver to receive

initial (coarse) frequency correction data. The length of time T_{fc} taken to receive this information depends on external influences and is therefore indeterminate. Once the data has been received it may be stored in the control circuit for quicker access, the stored data being compared from time to time with updating data from the source (usually a system controller or base station) to ensure that it remains current. In intervals 52 and 53, the frequency remains at the receiving frequency f_w of the WCDMA system.

At the end of interval 53, a coarse frequency adjustment is made depending on the received data, which data is applied to the phase-locked loop. This offsets the frequency of the signal output from the phase-locked loop by Δf_1 to give a frequency approximately equal to that of the GSM signals. This frequency offset is shown as a positive quantity in Figure 5, but it could be a negative quantity. The frequency offset Δf_1 is applied for the whole of interval 54, corresponding to a time period T_1 during which better synchronization data is received and a better frequency offset estimation is calculated. At the end of interval 54, once a fine frequency offset Δf_2 (which can also be either positive or negative) has been calculated, the fine frequency offset Δf_2 is applied to the phase-locked loop. The fine frequency offset offsets the frequency of the signal output from the phase-locked loop by Δf_1 to give a frequency substantially equal to that of the GSM signals.

This marks the beginning of interval 55, which lasts for a time T_2 . During interval 55 the receiver scans the GSM signal domain, and receives and decodes the GSM system information. The values of T_1 and T_2 are not fixed, because of the asynchronous nature of the signal reception during intervals 54 and 55, but T_1 and T_2 can be measured by the controller as they happen. The controller therefore also calculates a cumulative frequency error, which is the error introduced during the intervals 54 and 55, and calculates how long it will take (T_c) for a corrective frequency offset Δf_c to cancel that cumulative frequency error. The corrective frequency offset Δf_c is therefore applied in interval 56 for a period of T_c seconds.

By the end of interval 56 there will be substantially no frequency error in the operation of the phase-locked loop. Therefore in interval 57 the receiver is reconfigured so that the WCDMA receive chain is again receiving WCDMA signals from the WCDMA system. There is a short delay of duration before the receiver settles into a steady state and this is represented by the time period T_{PLL2} . Like T_{PLL1} the period of

time T_{PLL2} depends on characteristics of the phase-locked loop, but is essentially constant.

The corrective frequency offset Δf_c is calculated in the following manner. The cumulative error $\Delta\beta$ introduced during intervals 54 and 55 is a function of both frequency and time. Therefore:

$$\Delta\beta = T_1 \cdot \Delta f_1 + T_2 \cdot \Delta f_2$$

This has to be balanced by $T_c \cdot \Delta f_c$. It thus follows that

$$T_c \cdot \Delta f_c = T_1 \cdot \Delta f_1 + T_2 \cdot \Delta f_2.$$

Time periods T_1 and T_2 are set to be sufficiently long to ensure reception of GSM sync and system data and are therefore known. The time periods T_{PLL1} and T_{PLL2} are essentially constant and it follows that the end of interval 57 (when reception of WCDMA signals resumes) is at a known point in time. T_c is calculated working back from the end of interval 57 to the end of interval 55. The time period T_2 may be increased or decreased, if required, in order to ensure that reconnection to the WCDMA requires at the desired time (i.e. the end of interval 57). It is a simple matter of design to ensure that Δf_c is never so great as to cause the code phase of the receiver to drift outside the window W in Figure 3. Ideally, therefore, there will be no difference between the cumulative frequency error for a period of time during which a GSM scan is performed and one in which the mobile unit simply remains in standby. In practice, manufacturing tolerances may introduce a slight difference, but those same tolerances will make the receiver well able to cope with any small differences, which may therefore be ignored.

As will have been appreciated from the foregoing description the reference oscillator is allowed temporarily to achieve phase lock with the new system so that the receiver can scan the GSM signal domain and receive GSM data with the correct phase, so that no post correction is required. This approach requires very little overhead in circuit complexity, memory space and energy consumption. The error estimation is determined before returning to the WCDMA system and applied during the receiver re-configuration period, so that when the WCDMA system is re-acquired, the error is substantially reduced, if not completely eliminated.

Having thus described the invention by reference to a preferred embodiment it is to be well understood that the embodiment in question is exemplary only and that

modifications and variations such as will occur to those possessed of appropriate knowledge and skills may be made without departure from the spirit and scope of the invention as set forth in the appended claims and equivalents thereof.

CLAIMS:

1. A method of controlling a plural-mode receiver, capable of receiving signals from a first communication or signals from a second, different communication system, to reduce frequency errors associated with the receiver scanning for signals of the second communication system while receiving signals of the first communication system, the method comprising:

changing parameters of a reference oscillator of the receiver so that the oscillator oscillates at frequencies related to signals of the second communication system;

recording the change in frequency of the oscillator resulting from the adjustment;

receiving signals of the second communication system for a period of time; recording the period of time;

calculating from the recorded change and the recorded period of time an error vector; and

changing parameters of the reference oscillator, including applying the calculated error vector, so that the oscillator oscillates at frequencies related to signals of the first communication system.

2. A method as claimed in claim 1, further comprising:

receiving data relating to the frequencies of signals of the second communication system;

determining from the received data the parameters of the reference oscillator to cause the same to oscillate at approximately the frequencies related to signals of the second communication system.

3. A method as claimed in claim 2, further comprising:

receiving further data relating to the frequencies of signals second communication system;

determining from the received data corrections to be applied to the parameters of the reference oscillator to cause the same to oscillate at substantially the frequencies related to signals of the second communication system.

4. A method as claimed in claim 3, wherein the recorded change in frequency includes the change associated with oscillating at approximately the frequencies related to signals of the second communication system and the change associated with oscillating at substantially the frequencies related to signals of the second communication system.

5. A method as claimed in claim 3 or 4, wherein the period of time comprises both time spent oscillating at approximately the frequencies related to signals of the second communication system and time spent oscillating at substantially the frequencies related to signals of the second communication system.

6. A method as claimed in any preceding claim, further comprising receiving signals of the of the second communication system containing information pertaining to the second system.

7. A method as claimed in any preceding claim, wherein the scanning is effected while the receiver is in an idle mode.

8. A plural-mode receiver apparatus for receiving signals from a first communication or signals from a second, different communication system, the apparatus comprising:

a first receiver chain for receiving signals of the first communication system;

a second receiver chain for receiving signals of the second communication system;

a reference oscillator for generating a reference signal for the first receiver chain and the second receiver chain; and a controller for:

changing parameters of the reference oscillator so that the oscillator oscillates at frequencies related to signals of the second communication system;

recording the change in frequency of the oscillator resulting from the adjustment;

recording a period of time during which signals of the second communication system are received by the second receiver chain;

calculating from the recorded change and the recorded period of time an error vector; and

changing parameters of the reference oscillator, including applying the calculated error vector, so that the oscillator oscillates at frequencies related to signals of the first communication system.

9. An apparatus as claimed in claim 8, further comprising means for receiving data relating to the frequencies of signals of the second communication system and wherein the controller is arranged to determine from the received data the parameters of the reference oscillator to cause the same to oscillate at approximately the frequencies related to signals of the second communication system.

10. An apparatus as claimed in claim 9, further comprising means for receiving further data relating to the frequencies of signals second communication system, and wherein the controller is arranged to determine from the received data corrections to be applied to the parameters of the reference oscillator to cause the same to oscillate at substantially the frequencies related to signals of the second communication system.

11. An apparatus as claimed in claim 10, wherein controller is arranged to record changes in frequency that include the change associated with oscillating at approximately the frequencies related to signals of the second communication system and the change associated with oscillating at substantially the frequencies related to signals of the second communication system.

12. An apparatus as claimed in claim 10 or 11, wherein controller is arranged to calculate the period of time from both time spent oscillating at approximately the frequencies related to signals of the second communication system

and time spent oscillating at substantially the frequencies related to signals of the second communication system.

13. An apparatus as claimed in any of claims 8 to 12, wherein the controller is operable while the receiver is in an idle mode.

14. A receiver for receiving signals of a first communication system and signals of a second communication system, the receiver comprising a receiving circuit tunable to receive signals of the first and second communication systems, the receiver being arranged so that, while tuned to receive signals of the first communication system, the receiving circuit can be briefly retuned to receive signals of the second communication system before being tuned back to receive again signals of the first communication system, and so that a correction is made when tuning back to signals of the first communication system depending on tuning changes made while retuning and receiving signals of the second communication system and the duration of the changes.

15. A receiver as claimed in claim 14, wherein the receiving circuit comprises a first receiver chain operable to receive signals from a first communications system and a second receiver chain operable to receive signals from a second communications system.

16. A receiver as claimed in claim 15, further comprising a phase-locked loop circuit associated with the first receiver chain and with the second receiver chain.

17. A receiver as claimed in claim 16, wherein the phase-locked loop circuit comprises a single phase-locked loop configurable to output a signal at a first frequency related with signals of the first communications system or to output a signal at a second frequency related with signals of the second communications system.

18. A receiver as claimed in claim 16 or 17, wherein the phase-locked loop circuit comprises a voltage-controlled temperature-compensated crystal oscillator (VCTCXO) to which the correction is made.

19. A receiver as claimed in any of claims 15 to 18, wherein the first receiver chain is configured to receive signals of a continuous frequency division duplex system.

20. A receiver as claimed in any of claims 15 to 19, wherein the second receiver chain is configured to receive signals of a time division duplex system.

21. A receiver as claimed in claim 19, wherein the first receiver chain is configured to receive WCDMA signals.

22. A receiver as claimed in claim 20, wherein the second receiver chain is configured to receive GSM signals.

23. A receiver as claimed in any of claims 15 to 22, further comprising a controller for controlling the receiver circuit to cause the same to tune between the signals of the first and second communication systems.

24. A receiver as claimed in claim 23, wherein the controller is operable to calculate the correction from the tuning changes made while retuning and receiving signals of the second communication system and the duration of the changes and to apply the correction to the receiver circuit.

25. A method of receiving signals of a first communication system and signals of a second communication system, the method comprising tuning a receiving circuit to receive signals of the first communication system, retuning the receiver circuit to receive signals of the second communication system, tuning the receiver back to receive again signals of the first communication system, determining tuning changes made while retuning and receiving signals of the second communication system and the duration of the changes, calculating from the changes and duration of the changes a correction to be made to the tuning, and making the calculated correction when tuning back to signals of the first communication system.

26. An apparatus or method substantially as described herein with reference to the accompanying drawings.

1/4




Figure 1

2/4






Figure 2

3/4

Figure 3Figure 4

4/4




Figure 5

INTERNATIONAL SEARCH REPORT

International Application No

PCT/GB 03/04179

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 H04B1/16

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 6 122 506 A (LAU CHUNG Y ET AL) 19 September 2000 (2000-09-19) abstract; claims 15,18; figures 1,2	1,8,14, 25
A	US 5 841 396 A (KRASNER NORMAN F) 24 November 1998 (1998-11-24) abstract; claims 1,17; figure 6A	1,8,14, 25

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *G* document member of the same patent family

Date of the actual completion of the international search

9 January 2004

Date of mailing of the international search report

21/01/2004

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Kolbe, W

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/GB 03/04179

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 6122506	A	19-09-2000	TW 463511 B WO 9957929 A1	11-11-2001 11-11-1999
US 5841396	A	24-11-1998	US 5874914 A AU 2070297 A AU 5587698 A AU 5588898 A EP 1262790 A2 EP 0885492 A1 EP 0950194 A2 EP 0941487 A1 JP 2001505309 T JP 2001505665 T JP 2000506348 T US 2002084933 A1 WO 9733382 A1 WO 9825157 A2 WO 9825158 A1 US 6064336 A US 6133874 A US 6150980 A US 6400314 B1 US 6433734 B1 US 2001028321 A1 US 6208290 B1 US 5945944 A AU 723615 B2 AU 7662096 A BR 9611701 A CA 2230841 A1 CN 1211324 A , B EP 0855039 A2 JP 11513787 T WO 9714049 A2 US 6111540 A US 6002363 A	23-02-1999 22-09-1997 29-06-1998 29-06-1998 04-12-2002 23-12-1998 20-10-1999 15-09-1999 17-04-2001 24-04-2001 23-05-2000 04-07-2002 12-09-1997 11-06-1998 11-06-1998 16-05-2000 17-10-2000 21-11-2000 04-06-2002 13-08-2002 11-10-2001 27-03-2001 31-08-1999 31-08-2000 30-04-1997 28-12-1999 17-04-1997 17-03-1999 29-07-1998 24-11-1999 17-04-1997 29-08-2000 14-12-1999